



区域划分 Zoning	回路编号 Control Zone	控制方式 Control Type	灯具代码 fixture Code	品名 Discription	光源 Light Source	功率(W) Unit Watts	数量 Qty.	总功率 Total Load	备注 Remark
	董事长会议室	MR-AD1	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	8 ea.	800 W
		MR-AD2	DIM		吊灯	预留电源 1500W	1500 W	1 ea.	1500 W
		MR-AD3	DIM	LL1	LED 灯带	LED 10W/M	10 W	52 M	520 W
		MR-AD4	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	6 ea.	300 W
		区域功率 3120 W							
	会议室6	MR-BD1	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-BD2	DIM	LL1	LED 灯带	LED 10W/M	10 W	50 M	500 W
		MR-BD3	DIM		吊灯	预留电源 1500W	1500 W	1 ea.	1500 W
		MR-BD4	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	8 ea.	800 W
		MR-BD5	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-BD6	DIM	LL2	LED 灯带	LED 6W/M	6 W	3 M	18 W
		区域功率 3318 W							
	会议室5	MR-CD1	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-CD2	DIM	LL1	LED 灯带	LED 10W/M	10 W	50 M	500 W
		MR-CD3	DIM		吊灯	预留电源 1500W	1500 W	1 ea.	1500 W
		MR-CD4	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	8 ea.	800 W
		MR-CD5	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-CD6	DIM	LL2	LED 灯带	LED 6W/M	6 W	3 M	18 W
		区域功率 3318 W							
	会议室4	MR-ED1	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-ED2	DIM	LL1	LED 灯带	LED 10W/M	10 W	50 M	500 W
		MR-ED3	DIM		吊灯	预留电源 1500W	1500 W	1 ea.	1500 W
		MR-ED4	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	8 ea.	800 W
		MR-ED5	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-ED6	DIM	LL2	LED 灯带	LED 6W/M	6 W	3 M	18 W
		区域功率 3318 W							
	董事长会议室2	MR-FD1	DIM	LL1	LED 灯带	LED 10W/M	10 W	51 M	510 W
		MR-FD2	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	6 ea.	300 W
		MR-FD3	DIM		吊灯	预留电源 1500W	1500 W	1 ea.	1500 W
		MR-FD4	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	8 ea.	800 W
		区域功率 3110 W							
	会议室1	MR-JD1	DIM	LL1	LED 灯带	LED 10W/M	10 W	33 M	330 W
		MR-JD2	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	6 ea.	300 W
		MR-JD3	DIM		吊灯	预留电源 800W	800 W	1 ea.	800 W
		MR-JD4	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	6 ea.	600 W
		MR-JD5	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W
		MR-JD6	DIM	LL2	LED 灯带	LED 6W/M	6 W	2 M	12 W
		MR-JD7	DIM	LL2	LED 灯带	LED 6W/M	6 W	2 M	12 W

	区域功率 2304 W								
会议室2	MR-HD1	DIM	LL1	LED 灯带	LED 10W/M	10 W	34 M	340 W	
	区域功率 340 W								
会议室3	MR-GD1	DIM	LL1	LED 灯带	LED 10W/M	10 W	62 M	620 W	
	MR-GD2	DIM	AL7	嵌入式双头筒灯	MR16 50WX2	100 W	8 ea.	800 W	
	MR-GD3	DIM		吊灯	预留电源 1500W	1500 W	1 ea.	1500 W	
	MR-GD4	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	13 ea.	650 W	
	MR-GD5	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	5 ea.	250 W	
	MR-GD6	DIM	LL2	LED 灯带	LED 6W/M	6 W	2 M	12 W	
	MR-GD7	DIM	LL2	LED 灯带	LED 6W/M	6 W	2 M	12 W	
	区域功率 3844 W								
走廊	CO-D1	DIM	DL2	嵌入式筒灯	MR16 50W	50 W	18 ea.	900 W	
	CO-D2	DIM	DL2	嵌入式筒灯	MR16 50W	50 W	15 ea.	750 W	E为应急回路
	CO-D3	DIM	LL1	LED 灯带	LED 10W/M	10 W	133 M	1330 W	
	CO-D4	DIM	AL9	嵌入式筒灯	MR11 35W	35 W	11 ea.	385 W	
	CO-D5	DIM	LL1	LED 灯带	LED 10W/M	10 W	100 M	1000 W	
	CO-D6	DIM	DL2	嵌入式筒灯	MR16 50W	50 W	12 ea.	600 W	
	CO-D7	DIM	DL2	嵌入式筒灯	MR16 50W	50 W	9 ea.	450 W	E为应急回路
	区域功率 5415 W								
洗手间	TO-ND1	ON/OFF	AL3	嵌入式可调筒灯	MR16 50W	50 W	2 ea.	100 W	
	TO-ND2	ON/OFF	LL1	LED 灯带	LED 10W/M	10 W	7 M	70 W	
	TO-ND3	ON/OFF	LL1	LED 灯带	LED 10W/M	10 W	25 M	250 W	
	TO-ND4	ON/OFF	AL3	嵌入式可调筒灯	MR16 50W	50 W	14 ea.	700 W	E为应急回路
	TO-ND5	ON/OFF	LL1	LED 灯带	LED 10W/M	10 W	28 M	280 W	
	TO-ND6	ON/OFF	AL3	嵌入式可调筒灯	MR16 50W	50 W	13 ea.	650 W	E为应急回路
	区域功率 2050 W								
电梯厅	LL-D1	DIM	DL3	嵌入式筒灯	MR11 35W	35 W	8 ea.	280 W	E为应急回路
	LL-D2	DIM	DL2	嵌入式筒灯	MR16 50W	50 W	12 ea.	600 W	
	LL-D3	DIM	LL1	LED 灯带	LED 10W/M	10 W	31 M	310 W	
	LL-D4	DIM	LL1	LED 灯带	LED 10W/M	10 W	45 M	450 W	
	LL-D5	DIM	DL6	下照筒灯	LED 3W	3 W	10 ea.	30 W	
	区域功率 1670 W								
休息厅	RR-D1	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	13 ea.	650 W	
	RR-D2	DIM		吊灯	预留电源 800W	800 W	2 ea.	1600 W	
	RR-D3	DIM	LL1	LED 灯带	LED 10W/M	10 W	29 M	290 W	
	RR-D4	DIM		落地灯	预留电源 60W	60 W	3 ea.	180 W	
	区域功率 2720 W								
商务中心	BC-D1	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	6 ea.	300 W	
	BC-D2	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	4 ea.	200 W	
	BC-D3	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	8 ea.	400 W	
	BC-D4	DIM		吊灯	预留电源 800W	800 W	1 ea.	800 W	
	BC-D5	DIM		落地灯	预留电源 60W	60 W	2 ea.	120 W	
	区域功率 1820 W								
	VR-D1	DIM		吊灯	预留电源 800W	800 W	2 ea.	1600 W	

照明设备	VR-D2	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	4 ea.	200 W	
	VR-D3	DIM	AL4	嵌入式可调筒灯	MR16 50W	50 W	9 ea.	450 W	
	VR-D4	DIM	LL1	LED 灯带	LED 10W/M	10 W	31 M	310 W	
	VR-D5	DIM	LL2	LED 灯带	LED 6W/M	6 W	2 M	12 W	
	VR-D6	DIM		台灯	预留电源 60W	60 W	4 ea.	240 W	
	VR-D7	DIM		台灯	预留电源 60W	60 W	2 ea.	120 W	
	VR-D8	DIM	LL2	LED 灯带	LED 6W/M	6 W	2 M	12 W	
	区域功率								2944 W
总功率								39291 W	